

marantz®

MusicLink
SERIES

Marantz again amplifies its dedication to pure musical performance with the rebirth of the MusicLink Series. The aim is simple: to bring the listener all the emotion and musical detail of the original sound studio, combined with an elegant appearance and luxuriant feel. It is not a coincidence that the creator of the delightful new MusicLink Series is once again Ken Ishiwata.

HD-AMP1

INTEGRATED AMPLIFIER WITH DAC-MODE



70w X 2ch

DAC MODE

MARANTZ
musical digital
filtering

DSD
STREAMING

32 bit 384kHz

USB TYPE B
INPUT

COAX DIGITAL
INPUT

OPT DIGITAL
INPUT

Made for
iPod iPhone

HDAM SA2

SYMMETRIC
LAYOUT

CUSTOMISED
COMPONENTS

This newly-developed Marantz HD-AMP1 is a Premium-Class compact amplifier, with superb, elegant, classic looks. But don't let that misguide you, its current feedback technology blasts out an ear-splitting 70W at 4ohms, while its dual crystal clock and discrete DAC post filter with Marantz HDAM-SA2 modules make standard counted sound feel as incredible as high-resolution audio. This new amp also gives you the unique Marantz Musical Digital Filtering (MMDF), with two selectable filter characteristics to cater for different tastes and music. Each handles even the minutest of detail with loving care within the digital audio signal. As today's new media not only comes in 44.1kHz/16 bit resolution – similar to the CD format, Marantz developed the digital section to handle signals of up to 384kHz/32bit resolution and DSD 2.8MHz / 5.6MHz / 11.2MHz. Optical and coaxial digital inputs are ready to connect a TV or set-top box, and there is a USB-B port to stream music directly from your PC or MAC. iDevices can also be connected via the USB port on the front. To safeguard quality when connected to a computer, we built extended isolation around the USB-B input to eliminate the chance of high frequency noise generated by the computer entering the HD-AMP1. Information on volume, input, resolution, and more is shown on the stylish Marantz Porthole Display. While the solid aluminium front is supported by a double layer bottom plate and retro-style side panels. Welcome to the world of compact ecstasy.

Main Features

- Compact size Integrated Amplifier with digital inputs
- Current Feedback amplifier for pre-amplifier stage
- HDAM-SA2 & HDAM-SA3 for detailed audio reproduction
- Marantz Musical Digital Filtering
- 2x optical, coaxial and USB type B digital inputs capable of 384kHz/32bit high resolution audio including native DSD2.8/5.6/11.2
- High quality SABRE D/A converter
- Dual Clock for high digital accuracy
- Extended isolation for USB-B input to avoid computer noise distortion
- Gain control to support wide range of headphones
- Extended connectivity by 2 analogue inputs
- iDevice capable front USB input
- Marantz original speaker terminal SPKT-1
- Available in black & silvergold

EAN

EU	HDAMP1/N1B	4951035056905	Black
	HDAMP1/N1SG	4951035056882	Silvergold

UK	HDAMP1/N1B	4951035056905	Black
	HDAMP1/N1SG	4951035056882	Silvergold

www.marantz.eu



because music matters

HD-AMP1

INTEGRATED AMPLIFIER WITH DAC-MODE



FEATURES	HD-AMP1
DAC operation mode: USB / Coax / Optical	• / • / •
Asynchronous mode rear USB	•
Bit-perfect transmission	•
USB-B DSD Audio Streaming: DSD2.8 / DSD5.6 / DSD11.2	• / • / •
Ground isolator for DAC Mode operation	•
iPod / iPhone compatible USB input	•
DAC chip	SABRE ES9010KM2
HDAM version	HDAM+HDAM SA2
High Grade Audio Components	•
Customised Components	•
INPUTS/OUTPUTS	
Headphone Out	•
Headphone Volume Control	•
Headphone Gain Control (low / mid / high)	•
Analogue Input	2
Digital Optical In / Out	2 / -
Digital Coaxial In / Out	1 / -
Sample Rate digital In	192kHz/24bit
Speaker Terminals	2x Marantz SPKT-1
Gold plated Cinch	•
Front USB	•
USB type B input for Computer (back)	•
Asynchronous mode rear USB	•
Sample Rate USB type B In	384kHz/32bit
USB-B DSD Audio Streaming: DSD2.8 / DSD5.6 / DSD11.2	• / • / •
D-Bus	•

OTHER	
Power Output (8 / 4 Ohm RMS)	35W / 70W
Frequency Response	20 Hz - 50 kHz
Signal to Noise Ratio	105 dB
Total Harmonic Distortion	0,05%
GENERAL	
Available colours	Black / Silver-Gold
Remote Control	RC002HD
Power Consumption in W	55
Standby Consumption in W	0.3
Auto power off	•
Detachable Power Cable	•
Maximum Dimensions (W x D x H) in mm	304 x 352 x 107
Weight in kg	5.8



Design and specifications are subject to change by Marantz without notice.